

GİRİŞ AKIMLARI

<u>VOLT</u>	<u>AMPER</u>	<u>GİRİŞ VOLTAJI</u>	<u>GİRİŞ AKIMI</u>
24 V	15A	220 V	3A
24 V	20A	220 V	3A
24 V	25A	220 V	4A
24 V	30A	220 V	5A
24 V	40A	220 V	5A
24 V	50A	220 V	7A
24 V	60A	220 V	9A
24 V	70A	220 V	10A
24 V	80A	220 V	12A
24 V	90A	220 V	13A
24 V	100A	220 V	14A
24 V	110A	220 V	16A
24 V	120A	380 V	10A
24 V	130A	380 V	11A
24 V	140A	380 V	12A
24 V	150A	380 V	13A
24 V	160A	380 V	13A
24 V	170A	380 V	15A
24 V	180A	380 V	15A
24 V	190A	380 V	16A
24 V	200A	380 V	17A

<u>VOLT</u>	<u>AMPER</u>	<u>GİRİŞ VOLTAJI</u>	<u>GİRİŞ AKIMI</u>
48 V	30A	220 V	9A
48 V	40A	220 V	12A
48 V	50A	220 V	14 A
48 V	60A	380 V	10A
48 V	70A	380 V	12A
48 V	80A	380 V	13 A
48 V	90A	380 V	15A
48 V	100A	380 V	17A
48 V	110A	380 V	18 A
48 V	120A	380 V	19 A
48 V	130A	380 V	21 A
48 V	140A	380 V	23 A

48 V	150A	380 V	25A
48 V	160A	380 V 3 FAZLI	15 A
48 V	170A	380 V 3 FAZLI	16 A
48 V	180A	380 V 3 FAZLI	17 A
48 V	190A	380 V 3 FAZLI	18 A
48 V	200A	380 V 3 FAZLI	19A

<u>VOLT</u>	<u>AMPER</u>	<u>GİRİŞ VOLTAJI</u>	<u>GİRİŞ AKIMI</u>
36 V	30A	220 V	7A
36 V	40A	220 V	9A
36 V	50A	220 V	11A
36 V	60A	220 V	13A
36 V	70A	220 V	13A
36 V	80A	380 V	7A
36 V	90A	380 V	7A
36 V	100A	380 V	8A
36 V	110A	380 V	8A
36 V	120A	380 V	9A
36 V	130A	380 V	10A
36 V	140A	380 V	10A
36 V	150A	380 V	11A
36 V	160A	380 V	12A
36 V	170A	380 V	12A
36 V	180A	380 V	13A
36 V	190A	380 V	14A
36 V	200A	380 V	14A

<u>VOLT</u>	<u>AMPER</u>	<u>GİRİŞ VOLTAJI</u>	<u>GİRİŞ AKIMI</u>
72 V	60A	380 V	15A
72 V	70A	380 V	18A
72 V	80A	380 V	19A
72 V	90A	380 V	22A
72 V	100A	380 V	24A
72 V	110A	380 V	28A
72 V	120A	380 V 3 FAZLI	17A
72 V	130A	380 V 3 FAZLI	18 A
72 V	140A	380 V 3 FAZLI	20A
72 V	150A	380 V 3 FAZLI	21A

72 V	160A	380 V 3 FAZLI	23A
72 V	170A	380 V 3 FAZLI	24A
72 V	180A	380 V 3 FAZLI	26A
72 V	190A	380 V 3 FAZLI	27A
72 V	200A	380 V 3 FAZLI	29A

<u>VOLT</u>	<u>AMPER</u>	<u>GİRİŞ VOLTAJI</u>	<u>GİRİŞ AKIMI</u>
80 V	30A	220 V	14A
80 V	40A	380 V	11A
80 V	50A	380 V	14A
80 V	60A	380 V	17A
80 V	70A	380 V	19A
80 V	80A	380 V	22A
80 V	90A	380 V	25A
80 V	100A	380 V 3 FAZLI	16A
80 V	110A	380 V 3 FAZLI	18A
80 V	120A	380 V 3 FAZLI	19A
80 V	130A	380 V 3 FAZLI	21A
80 V	140A	380 V 3 FAZLI	22A
80 V	150A	380 V 3 FAZLI	24A
80 V	170A	380 V 3 FAZLI	27A
80 V	180A	380 V 3 FAZLI	29A
80 V	190A	380 V 3 FAZLI	30A
80 V	20 A	380 V 3 FAZLI	32A